



MIR-AUS®
MIR PRESS
Digital Transfer Solution

Tel: +61 2 8065 5614
www.mir-aus.com.au
info@mir-aus.com.au


Heat Press Hest HT-M38 8-in-1 Multi-functional 38x38cm




CONTENTS

I. Assembly Drawing	2
II. Technical Parameters	2
III. Operation Process	3-5
IV. Maintenance	6
V. Trouble Shooting For Transfer Print Quality	6
VI. Circuit Diagram	7
VII. Explosion View	8


I. ASSEMBLY DRAWING



- ① Power Switch
- ④ Electrical Case
- ⑦ Under Plate



- ② Fuse
- ⑤ Handle Bar Grip
- ⑧ GY-05 Digital Controller




- ③ Power Cord
- ⑥ Flat Heat Platen
- ⑨ Hand Wheel

II. Hest HT-M38 8-in-1 Technical Parameters


1. **Model No.:** Hest HT-M38 8-in-1
2. **Machine Size:** 590*580*390mm
3. **Heat platen Size:** 15"x15" (380x380mm)
4. **Printable Articles Max Size:** 380*380*30mm
5. **Voltage:** 220v/1Phase/120v/1Phase
6. **Power:** 2kw Heating tube power: 1.8kw*1/1.2kw
7. **Maximum Time.:** 0-999C
8. **Recommend Setting:** 30~280s; 180~200°C
Time Range: 0~999s
Maximum Temp: 225 C
9. **Packing Size:** 700*700*500mm
10. **Gross weight:** 55kg

III. Operation Process



1. How to exchange the heat element Plate Heat Element



Please loosen the screws marked in red



Disconnect the wire socket as the above picture show




Remove the heat platen and install the plate heater
Tighten the screws of plate heat element and connect the wire socket



MIR-AUS®
MIR PRESS
Digital Transfer Solution


Tel: +61 2 8065 5614
www.mir-aus.com.au
info@mir-aus.com.au

Mug Heat Element




Disconnect the heat platen wire. Connect the mug press, one socket is power socket
The other one is limit switch socket

Cap Heat Element



Loosen the screws marked in red

Remove the heat platen and
under plate











(The machine is like the above
picture now







Tighten the screws (marked in red
of cap heat element, then
the wire

IV. Operation Process

1. Set temperature required

		
<p>Turn on power switch, temperature light is ON. The digital display shows</p> 	<p>Press  button, the  light is on (C denotes Celsius). Press arrows "△" or "▽" to select "°C" or "°F" (F denotes Fahrenheit) according to your habits.</p>	<p>Press  button, the temp  light is on. Select with arrows the temperature according to different transfer material (Normally 180°C~200°C)</p>

2. Set time required

		
<p>Press  button after temperature setting and the  time light is on. Select with arrows the time according to different transfer material.</p>	<p>Press  button after time setting; the display shows the temperature starts to rise. "CD-L" shows the time counting down during your transfer.</p>	<p>Note: There are two small port in front side of the digital display. If the real temperature is lower than digital controller shown, you can adjust the "hot port"; Clockwise to raise temperature; anticlockwise to reduce temperature.</p>

3. Printing methods

Step 1: Make sure the cord is connected well to the wall socket. Place the object (i.e. T-shirt) on press bed, and transfer paper with images facing down the object, adjust pressure to your requirement, and turn on the power.

Step 2: Set the temperature and time required, then temperature starts to rise.

Step 3: When the temperature rises to the setting temperature, the buzzer sends out sounds; then close down heat platen (meantime the sounds stop) and starts to transfer.

Step 4: Then the time counter is on, once time is up, the buzzer will send out sounds again; then lift up the heat platen, meantime the sounds stop. Transfer work finished.



Tel: +61 2 8065 5614
www.mir-aus.com.au
info@mir-aus.com.au

Step 5: Consult the Transfer Paper instructions on whether to peel cold or hot, Here are suggested Pressing time guidelines for different transfer paper.

Ink-Jet Transfer Paper (fabric) 14-18 seconds
Laser Copier/Printer Transfer Paper (fabric) 18-25 seconds
Sublimation Transfers (onto Fabrics) 25-30 seconds
Sublimation Transfers (onto FR-Plastic/Woods) 60-70 seconds

Note: pls use the similar way to transfer other items after you exchange the heating elements. But the printing parameters are different from different items. You can refer to below.

5. Recommendations:

1) Ceramic tile transfer: (Mugs & Plates transfer is similar)

Set temperature: 180°C

Set time: 15 seconds

2) Cap transfer:

Set temperature: 180°C

Set time: 60 seconds

3) T-shirt transfer:

Set temperature: 180°C

Set time: (chemical fiber use for sublimation transfer paper: 30-50seconds; pure cotton use for T-shirt Transfer paper: 10-20seconds)

NOTE:

- 1) Please switch off the machine and unplug the power cord when the machine is not in use.
- 2) The heat platen will cool down to the room temperature, if heat press stays un-use for more than 30 minutes.
- 3) The heat-releasing fan will automatically starts when the temperature of heat platen reaches 80 degree C (176 degree F). It helps to reduce the temperature of electrical parts and prolong the service life of them.
- 4) For better maintenance of heat press, the maximum setting temperature is 210 degrees C (410 degrees F).
- 5) To avoid re-heating the first transfer when printing double sided T-Shirts, insert a sheet of cardboard in between the shirt, adjust the height to less pressure, then press.
- 6) Heat platen may pivot slightly back and forth rotationally. This is due to movement allowance within the clamp Assembly, and is normal.

V. Maintenance

1. No action after turning on the machine

- 1) Check the plug whether it connects well or whether it is broken.
- 2) Check the power switch or digital controller whether it is broken.
- 3) Check the fuse whether it has been burnt out.
- 4) Indicating light is on, but no display on screen, check the 5 cable of Railway transformer. If it's loosening, showing the problem is poor connection. If they connect well, showing that the Transformer is faulty.

2. The display screen are working well, but no temperature increasing on the heat platen.

- 1) Check whether the thermocouple of the heat platen touches well. If the thermocouple is loose, the display will show 255 and machine keeps beeping.
- 2) Check if the indicating light of solid-state relay is on, if not, check if the relay or digital controller is broken.
- 3) If you already changed the new solid-state relay but the heat platen still can't be heating up, check if the heat platen is faulty or the heat platen's power cable is loose, need to change by new heat platen.

3. The heat platen works well, but suddenly the display screen show 255°C.

- 1) Check whether the thermocouple of the heat platen touches well.
- 2) If the thermocouple touches well but still show 255°C, then it is faulty.

4. The machine is heating during 0~180°C, but display number jumps to above 200°C or 300°C suddenly, or the numbers on display jumps irregularly.

- 1) Check whether the thermocouple of the heat platen touches well.
- 2) If the thermocouple is good, it shows that the program of digital controller is broken, which namely IC or is broken, need to change by new controller.

5. The temperature is out of control: Set 180°C, but the actual temperature is above 200°C.

- 1) It means the solid-state relay is broken, out of control, need to change the relay.
- 2) Or the digital controller is faulty, and it keeps conveying electric to relay, need to change controller.

6. The setting temp and time becomes abnormal after exchange the heat platen

- 1). Please reset the temp and time according the operation process manual.


7. Other notice

- 1) In order to prolong the machine service life, please add the lubrication oil regularly on the joints.
- 2) In order to keep the heating elements' good transfer effect, you need to protect the heat platen carefully whenever you are using it or not.
- 3) Please keep the machine in dry place.
- 4) If you are not able to solve the electrical parts problem, please kindly contact the supplier and get Technical support.

VI. Trouble shooting for transfer print quality

1. If the print color is pale: the temperature is too low / the pressure is not correct / or not pressed long enough.
2. If the print color is too brown or the transfer paper is almost burnt: reduce the setting temperature
3. If the print is blurring: too much transfer time causes proliferation.
4. If print color is different/ partial transfer effect is not good enough: the pressure is not enough / or not pressed long enough / or poor-quality transfer paper.
5. If transfer paper stick to the object after transfer: the temperature is too high/ or poor-quality printing ink.

VI. Circuit Diagram




K: Power switch
SA: Limit Switch

FU: Fuse
SJ: Digital Controller

R1: Relay

VII. Explosion View



No.	Part Name	Qty
1	Machine base	1
2	Column	1
3	Power Cord	1
4	Electrical Parts Bracket	1
5	Electrical Case	1
6	Fuse Holder	1
7	Power Switch	1
8	Electrical Case Paper Part	1
9	Electrical Case Cover	1
10	Serpentuator	1
11	Swing Arm	1

No.	Part Name	Qty
12	Support Shaft	1
13	Handle	1
14	Adapter Plate	1
15	Heating Plate Cover	1
16	Compression Spring	1
17	Connecting Plate	1
18	Adapter Plate	1
19	Heat Platen	1
20	Under Plate	1
21	Support Plate	1
22	Shield for Column	1